

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18RK121SN1# from the official website of Murata Manufacturing

## BLM18RK121SN1#

"#" indicates a package specification code.







< List of part numbers with package codes > BLM18RK121SN1D BLM18RK121SN1J BLM18RK121SN1B






Packaging

# Packaging Information

Specifications









: Electrode

	·	Quantity
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000
В	Bulk(Bag)	1000



Other Usage

For general

1 of 4

Minimum Order

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18RK121SN1# from the official website of Murata Manufacturing
Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM18RK121SN1%23

## BLM18RK121SN1#

"#" indicates a package specification code.



The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_R series can be used in a digital Interface. Resistance of BLM\_R series especially grows in the lower frequency range. Therefore BLM\_R series is less effective for digital signal waveform at low frequency range and can suppress the ringing.

2 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date.  ${\bf Please\ download\ the\ latest\ data sheet\ of\ BLM18RK121SN1\#\ from\ the\ official\ website\ of\ Murata\ Manufacturing}$ Co., Ltd.

## BLM18RK121SN1#

"#" indicates a package specification code.



Shape	SMD
Size Code (in mm)	1608
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Impedance (at 100MHz)	120Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	200mA
Rated Current (at 125°C)	200mA
DC Resistance(max.)	0.25Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1

3 of 4

### Attention


1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.




## BLM18RK121SN1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

4 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

